

The company Monange was founded in 2017 after 10 years of research and development and offers a new listening experience thanks to its Smart Bias technology. Putting the power and the precision of the digital electronics in the service of vacuum tubes, it makes it possible to propose reliable, robust, powerful amplifiers with unprecedented features.



The Promesse 34 is our first achievement with this technology. This integrated amplifier is based on a push-pull of EL 34 tubes in class AB and provides a power of 35 Watts.

You will be able, in a completely new way, to change the bias currents as simply as turning a knob, even while listening, and thus adapt the tone of your amplifier to your music.

## TECHNOLOGY

- » Unique Smart Bias™ Technology
- » Digital volume control
- » Analog-regulated high-voltage power supply
- » DC and EMC filter for mains Read
- » Mains surge protection handling up to 2,500 A

## OUTPUT

- » 2 x 35Watts RMS at 1Khz
- » Bandwidth: 10Hz - 85 KHz
- » Output impédance : 4, 8, 16 Ω

## INPUTS

- » 3 analog RCA (2 V)
- » 2 digital inputs type S/PDIF optical - 24 bits 196 KHz
- » 2 digital inputs type RCA with transformer insulation - 24 bits 196 KHz
- » 1 USB Interface - 24 bits 196 KHz

## TUBES

- » 4 x EL34 (power tubes)
- » 2 x 12AX7 (input stage / phase shift)

## OPTIONS

- » BlueTooth Interface - 24 bits 48 KHz.

## DIMENSIONS AND WEIGHT

- » Dimensions (Width x Height x Depth) : 17" x 10" x 14.8"
- » Weight : 50 lbs

## ELECTRICAL SYSTEM

- » Power input : 120 VAC 60 Hz
- » Power consumption : 120 W

## STANDARDS AND CONFORMITY

- » IEC 62368-1
- » EN 50581
- » EN 50564

MONANGE SAS  
SAS au capital de 13200 euros.  
Société immatriculée au R.C.S de Saverne  
SIREN : 832 726 681  
1, rue Gambrinus 67190 Mutzig, France

All our products are handmade in France  
with the highest quality standards

Visit our website  
[www.monange-audio.com](http://www.monange-audio.com)

